カルマン渦式 流量センサ

KSL-5/10/30/50L

取扱説明書



URL http://www.rgl.co.jp 概要

〒252-0331

流量センサKSL-5/10/30/50Lは、高い精度で 流量と温度を検出し、表示します。同時に アラーム信号・アナログ信号・パルス信号を 出力することができます。 接液部が耐熱樹脂製で、高温流体の測定が

RGI 株式会社 JOINT リガルジョイント

神奈川県相模原市南区大野台1-9-49

TEL 042-756-7411(営業ダイヤルイン)

FAX 0120-85-7411(**図**フリーダイヤル)

可能。デジタル調整によりアラーム設定が

ご使用前に

- ●本製品を使用する前に、必ず取扱説明書を読んで内容を理解して下さい。
- ●取扱説明書で指定した使用方法、使用条件、注意事項を必ず守って下さい。

安全上のご注意 この取扱説明書で使用している表示と意味は次の通りです。

誤った取扱いをしたときに、死亡や重傷等の ※告 誤った取扱いをしたことに、加上 重大な結果になる恐れのあるもの。

絶対に行なわないで下さい。 必ず指示に従い、行なって下さい。

⚠ 警告

● 煙が出ている、変なにおいがする、動作が不安定など異常・故障状態のまま使用すると火災、事故の原因となります。 このような時はすぐに電源供給をやめ、販売店に状況をご連絡下さい。お客様による分解修理は絶対におやめ下さい。 使用環境

- 湿気や結露の多い場所で使用すると水分が内部にたまり事故・故障の 原因となります。
- ◇ 震動、衝撃、脈動を受ける場所で使用すると、不正動作・事故・故障の 原因となります。
- ◇ 本製品は防爆構造ではありませんので、可燃性ガス、爆発性ガス、腐食性ガス雰囲気等の危険な場所では使用しないで下さい。 反対 屋内設置用に設計されていますので、屋外では使用しないで下さい。
- 熱器具などの高温となる場所で使用すると内部の温度が上昇し事故・故障の原因となりますので、使用条件の下でご使用下さい。

⚠ 注意

ケーブルの取扱い

- ケーブルに重いものを乗せたり、センサ本体からケーブルを引っぱったりすると事故・故障の原因となります。
- 使用していないケーブル同士、又はケーブルと外部機器が接触すると事故・故障の原因となりますので、1本ずつ絶縁処理をしてからご使用下さい。
 配線の際、出力の負荷条件、電源電圧の許容差が本書に記載された範囲外になっていると事故・故障の原因となりますので、『配線方法』『出力信号』『仕様』の項目に記載された内容を必ずお守り下さい。

- 磁気や電磁波、放射線、紫外線のあたる場所で使用すると事故・故障の 原因となります。
- 電食の影響や静電気が帯電するような場所で使用すると、事故・故障の原因となります。
- 高周波電源周辺等電気的ノイズの影響を受けるような場所で使用すると、 事故・故障の原因となります。
- 流体内に金属片、シールテーブ等の異物が混入する恐れのある場合、必ず上流側にフィルタを設置して下さい。

■ 配管作業時など、センサ本体に指をはさむとケガの原因になりますのでご注意下さい。

開梱、持ち運び

→ 開梱や持ち運びの際、落とさないように行なって下さい。センサ本体が落下し事故・故障の原因となります。 設置作業

⚠その他

▶ 開梱時、中の製品に損傷や変形を発見した場合は、使用しないで販売店に状況をご連絡下さい。

保 守

保守点検

- 表示カバーの内部には電子基板があり、触ると事故・故障の原因となります。 内部の点検・調整・修理は販売店にてご依頼下さい。
- 配管、配線作業、及び保守、点検は専門知識と経験を持った担当者が行なって下さい。 ● 安全のため、水・電源の供給を止め、配管内を無加圧状態にしてから行なって下さい。

保管方法

- 弊社製品を保管される場合は、以下に記す条件を満たす場所で保管して下さい。 雨、水のかからない場所。・直射日光の当たらない場所。・粉塵のない場所。
- 振動、衝撃のない場所。・静電気対策がされている場所。 周囲温度0~40℃の空調管理されている(結露、凍結しない事)場所。 ※ 弊社出荷時の梱包状態のまま保管願います。

保証及び免責事項


- ●弊社製品の誤った使用、不適切な使用により発生した事故に関しましては、弊社は責任を負いかねますのでご了承下さい。 ・弊社製品についての保証期間は、製品納入から1年間となります。
- ・保証期間内での性能及び材質の不具合に対して、弊社責による原因であると弊社が文書で承認した場合、 代替品を提供させていただきます。
- Nganeを使いていていています。 尚、此処での保証範囲は弊社製品単体に限定されます。製品の故障により直接あるいは間接的に起こる損失
- 同、 LLM2 Cの休証制団は学社 装配甲特に民族とれます。 表記の200階により国政の30 いは同政がに成こる打木、 損傷、怪我、その他を含めた損害に関しては保証の対象範囲から除外します。 ・要求により先行で代替品を提供、その後の不具合の原因調査により、弊社責でない事が判明した場合、代替品は 有償となります。 ※代替品は基本的に同製品となりますが、弊社製造上の都合により同等品となる場合があります。
- ※弊社責外となる不具合要因例について以下に記します。
 ・取扱説明書(最新版)に記載している内容以外での使用。 使用上の不注音

取扱説明書について


- *性能改善のため、形状・仕様を予告なく変更することがありますのでご了承ください。


構 成・寸法図

下図のように、接液部であるボディトに電子回路(基板)を組み込んだカバーを取り付けています。 カバー上部には流量・温度を設定する操作パネル、表示LEDがあります。



注) 単体取付けブロックは取付け寸法により、背面を固定(2個のM4 皿小ネジ使用) 底面を固定(4個のM4六角穴付ボルト使用)或いは、パイプによる固定などが可能です。





*1 アダプタの口径は、注文時の選定により決定します。 *2 KSL-50Lは Rc1/2 のみとなります。

仕 様

型式		KSL-5L	KSL-10L	KSL-30L	KSL-50L	
定格流量範囲	∄	0.5~5.0L /min	1.5~10.0L /min	5.0~30.0L/min	7.0~50.0L /min	
適用流体		工業用水・水				
検出方式			カルマン渦式			
流体温度			0~9	0℃		
周囲温度			0~40℃ (無凍結時)		
温度計測範囲	∄		0~1	200		
精度			±2.09	%F.S.		
最高使用圧力	כ		1.01	1Pa		
*3 電源電圧			DC12V±5% or	DC24V±10%		
消費電流 MAX30mA (但し4~20mA 電流出力時MAX70mA)		'0mA)				
ケーブル		AWM20276 9芯/0.2mm ² /500mm				
アナログ出力	流量	0∼10V or 4∼20mA/パルス				
1	温度		0∼10V or	4~20mA		
アラーム出力		オープンコレクタ A・B(流量、温度)				
表示方式	数値	流量 3桁LED 温度 2桁LED				
12/10/11/	点灯	アラーム2色LED				
認証、規格な	۳	RoHS指令 (SUSアダプタ仕様のみ)				
接液部材質		流量部/PPS、 測温部/SUS304				
接続部材質	接続部材質		SUS or BsBN	1 (Niメッキ)		
シール用0リン	/ グ		クロロプレンゴム	ı or フッ素ゴム		
配管口径		Rc3/8 or Rc1/2				
質量			約39	0 g		

*3 電源電圧は、注文時にDC12VまたはDC24Vのいずれかが選択できます。

配管について



- 配管は配管用アダプタにねじ込むか、弊社製品のカンタッチ継手等を使用して行ないます。
- 配管材の取り付けの注意
 - スパナ(35mm)をかける時は、必ず配管用アダプタの外周を使用して下さい。

⚠注意 取付ブロックに直接スパナをかけますと、破損する恐れがあります。

- 配管用アダプタの内径は、Rc3/8ネジ or Rc1/2ネジになっています。
- 配管用アダプタは、六角穴付ボルトM4×8 4本で取付ブロックに固定されています。 取付け取外しには、3mmの六角ドライバーかL型レンチを使用します。

⚠注意 流量センサ本体と配管用アダプタ間のシール面には、**0リング** P16が入っています。 取付け忘れや噛み込み及びゴミなどが入らぬよう充分ご注意願います。

⚠ 警告

- 0リングを挿入しないで取付けた場合、水漏れを起こしますのでご注意下さい。
- 水の汚れが目立つ場合は、配管にフィルターを装着して下さい。
- 流体感知部のゴミ溜りの原因となり、センサの故障につながります。 (ご相談に応じてフィルターもご用意致します)

配線方法(インターフェース)

中継端子、コネクタなどにハンダ付け、または圧着により接続してください。コネクタのとき、芯線サイズ#24~#28を推奨します。

★ 警告 未使用線は、端末処理してください。

【各ケーブル機能】


	27VIX.001				
色	名称	特性	出力選択 * 4	動作・使用法	
赤	電源+	DC24V±10% DC12V±5%	2者択一	装置によりDC電源を供給。 KSLに電源スイッチはなく即時に電流が流れる。	
黒	電源-	GND		共通アースライン。この一本で電源を始め ほかのすべてのラインの共通帰路になる。	
白	アナログ出力 パルス出力 (流量)	字 0~10V 号 4~20mA パルス出力 DPM	4者択一	流量を電気信号に置換して 装置側に送信する。	
橙	アナログ出力 (温度)	0~10V 4~20mA	2者択一	水温を電気信号に置換して 装置側に送信する。	
黄	アラーム (流量)	オープンコレクタ (A) オープンコレクタ (B)	2者択一	流量が設定値を越えたとき装置側へ通報。 (A): 流量≥設定値でON (B): 流量<設定値でON	
緑	アラーム (温度)	*5 オープンコレクタ (A) オープンコレクタ (B)	2者択一	温度が設定値を越えたとき装置側へ通報。 (A):温度≥設定値でON (B):温度<設定値でON	
灰青茶	予備芯			予備さ。 通常は使用しておりません。	
*4	*4 出力選択に示されるものは、注文時にいずれか1つの仕様が選択できます。				

- *5 アラーム出力(A)=オフ出力、アラーム出力(B)=オン出力

使用していないケーブル同士、又はケーブルと外部機器が接触 すると事故・故障の原因となりますので、1本ずつ絶縁処理 をしてからご使用下さい。

- 電源供給(1)仕様より過大な電圧を与えると破壊します。
 - (2) 逆極性接続をすると破壊します。
- ・アナログ出力 出力線が電源にショートすると破壊します。 アラーム出力


【負荷の取り方】 装置側負荷抵抗 (RL) の標準的な取り方を示します。




⚠注意・リレー負荷時、逆起電力によるトランジスタの破損防止のため。 ダイオード内蔵リレー(D)をご使用下さい。

・アナログ出力は、出荷時に電圧または電流出力のいずれかに 設定されていますのでご確認の上ご使用下さい。

出力信号




パルス出力 【Ⅰ】パルス出力



※主に積算流量を測定する為のバルス仕様となります。


:KSL-10/50Lでは選択できない仕様となりま				ま9
		KSL-5L	KSL-30L	
出力方式		オープンコレクタ		
バルス	形状	上図参照(パ	ルス幅固定)	
単位パ	ルス	0.001L/P	0.01L/P	
備	考	リレー負	荷無効	



※弊計指定の外部表示器「DPMIを使用する為の パルス仕様となります

	KSL-5L	KSL-10L	KSL-30L	KSL-50L
出力方式	7	オープンコレクタ		
バルス形状	上図参	上図参照 (パルス幅変動)		
備考	リレー負荷無効			


操作方法



【操作方法】

流量設定

1. インターフェースケーブルを接続後、直流電源を投入すると、動作がスタートし、流量モー ドとなります。 (電源スイッチはなく、DC24Vまたは12Vへの接続により立ち上がります)



- 2. ①流量スイッチを押下すると、⑥表示LEDが点滅し、アラーム設定が有効になります。 ⑤設定スイッチ の押下により、しきい値が増加します。目標のしきい値に達したら、再び① 流量スイッチを押下すると、しきい値が確定し、流量表示に戻ります。
- 4. ①流量スイッチ を押下しながら⑤設定スイッチ を押下すると、しきい値は減少します。

実際の流量がしきい値をオーバーすると、

<表LンアラームAの場合は ③流量アラーム表示LED が赤色から緑色に変わり、ケーブルのアラーム信号をオンにします。(注文時、逆極性選択も可。)

※流量 F 表

が以下の値を超えると 示になります。			アラーム出力	と表示し
			計測値	Α
L-5L	6L/min		DI NOME	緑古竹ノ
L-10L	12L/min		設定値以上	**********
L-30L	40L/min			/ ON
L-50L	60L/min		設定値未満	赤点灯
	,		政Æ順本冊	/OFI

LEDの定義 弊社では、アラーム出力と表示LEDの 定義を<表1>に定めております。 用途に併せ、ご注文の際にご指定 頂いています。 赤点灯

*アラーム出力はオープンコレクタで ONが導通、OFFが非導通です。 *アラームは流量、温度、単独で選定 することが出来ます。

KS

- 1. ②温度スイッチ を押下すると温度モードに移ります。右図のように、 2 桁表示で、単位を g で表示します。
- 2. 再び②温度スイッチを押下すると⑥表示LED が点滅し、温度アラーム設定が有効になります。 3. ⑤設定スイッチ の押下により、しきい値が増加します。
- 4. ②温度スイッチ の押下にてしきい値が確定し、温度表示に戻ります。


水温がしきい値をオーバーすると、

<表1>アラームAの場合は ④温度アラーム表示LED が赤色から緑色に変わり、ケーブルのアラーム 信号をオンにします。(注文時、逆極性選択も可。)

※確定範囲は0~99℃であり、ヒステリシスはもちません。

☆ 唯元 羊5四 180 ・ ララ C	このう、こハノ フュ	/////
オーバーレンジ表示	F (100℃以上)	
	0 (0℃以下)	

流量特性



- 流量特性は、下図のように温度依存性をもちます。
- ・精度を落とさないため、直管長は F流側 7 D F流側5D以上を確保してください。 (D: 口径 5LはD=4.1mm、10LはD=5.8mm 30L(\$\dagger{z}D=10mm, 50L(\$\dagger{z}D=12mm)
- 上流側の配管サイズを(オリフィスなどを入れて)
- 急激に変えるような配管はしないでください。 0 0.5 1 2 3 4 5 KSL-5L・弁、分岐、ゲージ等も下流側へ設置してください。 0 1 2 4 6 8 10 KSL-10L

0 3 6 12 18 24 30 KSL-30L 0 5 10 20 30 40 50 KSL-50L 流量 (L/min)

メンテナンス 【センサ本体の取り外し】

- (1) 電源をOFF にして下さい。(本機には電源スイッチは設置されていませんので、
- 電源ケーブルを取り外して下さい) (2) 3mmの六角ドライバー、或いは6角棒レンチでアダプタ用のM4ネジ(六角穴付きネジ M4×8) 4本をゆるめます。
- ・アるのよす。 (2)項でゆるめたアダプタ側へ少しずらします。
- (4) アダプタとセンサ本体の間に隙間ができ、本体のブロックのト側、或いは手前側に 引き抜くことができます。その際、配管内の水が流出する恐れがありますのでご注意下さい。 また、両側のOリングを落とさぬように注意して下さい。
- (5) 取り付けは、取り外しの逆の手順で行います。

⚠注意 両側のOリングは忘れずに必ず取り付けて下さい。

*メンテナンス上の不明点等ございましたら弊社までお問い合わせください。 製品の解体、分解による故障が認められる場合は、責任を負いかねます。

製造元 株式会社リガルジョイント

TEL 042-756-7411 (営業ダイヤルイン) 0120-85-7411 (ゴブリーダイヤル)

第13版 2014年8月

Karman Vortex JOINT CO., LTD. **Flow Meter**

KSL-5/10/30/50L



1-9-49 Onodai Minami-ku Sagamihara-shi Kanagawa Japan 252 0331 Tel: +81-42 756 7411 Fax: +81-42 752 2004

URL: http://www.rgl.co.jp

Overview

The flow meter KSL-5/10/30/50L detects and displays the flow rate and temperature with high accuracy. At the same time, the KSL-5/10/30/50L can output alarm signals, analog signals, and pulse signals. Because the liquid contacting part is made of a heat-resistant resin, high-temperature fluid can be measured. By digital adjustment, alarm can be set easily.

Before use

•Before using this product, be sure to read the Operation Manual and understand the instructions in it. •Be sure to observe the use method, use conditions, and precautions specified in the Operation Manual. Safety precautions
The symbols used in this Operation Manual and their meanings are as follows:

This symbol indicates that misuse of the unit could lead to death or serious injury.

This symbol indicates a prohibited action. This symbol indicates a compulsory action

MARNING MARNING

Occurrence of abnormalities and malfunctions

Continuing to use the unit in abnormal or defective conditions such as smoke, strange smell, or instable behavior may lead to fire or accident. In this case, disconnect the power supply immediately and notify the dealer of the state. Under no circumstances should you try to disassemble and repair the product yourself.

O Do not use this product in places where moisture or condensation is present. Doing so may cause the product to collect moisture in it, resulting in an accident or malfunction.

O Do not use the product in places subject to vibration, shock, or pulsation. Doing so may cause an illegal operation, accident, or malfunction.

or corrosive gas atmosphere is present. This product is designed to be installed indoors. Do not use it outdoors.

Do not use this product in a location subject to high temperatures such as near a heater. Doing so may increase the temperature inside the product, resulting in an accident or malfunction. Use this product under the use condition.

A CAUTION

Handling of cables

- O not place heavy objects on cables or pull a cable from the meter unit. Doing so may cause an accident or malfunction
- If cables not in use come in contact with each other or a cable comes in contact with external equipment, an accident or malfunction may occur. Be sure to insulate each cable before use.
- If the load conditions of output or the tolerance of the power supply voltage is out of the range described in this manual, an accident or malfunction may occur. Be sure to observe the instructions described in the section of "Wiring method," "Output signals," and "Specifications".

- O Do not use the product in a place that is exposed to electromagnetic waves, radiation, ultraviolet rays. Doing so may cause an accident or malfunction.
- O not use the product in a place that is affected by electrolytic corrosion or where static electricity is charged. Doing so may cause an accident or malfunction. O Do not use the product in a place that is affected by electrical noise such as the vicinity of
- a high-frequency power source. Doing so may cause an accident or malfunction. If there is a possibility that foreign substances such as metal pieces or seal tape are mixed into the fluid, be sure to install a filter on the upstream side.
- If air bubbles are mixed in the fluid, correct measurement cannot be performed. Remove air bubbles completely before using the product.

Unpacking and carrying

When unpacking or carrying the product, be careful not to drop it. If the meter unit drops, an accident or malfunction may occur. Installation

Be careful not to pinch your fingers in the meter unit during piping, etc. Doing so may cause injury.

⚠ Other

🚫 If you detect damage or deformation of the product in the package when unpacking it, contact your dealer and explain the situation without using it.

Maintenance

Maintenance and inspection

The display cover is incorporated with an electronic substrate. Touching the substrate could result in an accident or malfunction. Entrust your dealer with the inspection, adjustment, and repair of the product.

 Piping and wiring work, maintenance, and inspection should only carried out by personnel with expertise and experience For safety reasons, stop the supply of water and power and put the inside of the pipe to a non-pressurized state before starting maintenance and inspection. Storage method

- When storing our product, store it in a place that meets the following conditions.
- A place that is not subject to rain or water A place without direct sunlight A place without dust A place without vibration and impact - A static-free area
- A place air-conditioned to an ambient temperature between 0 and 40°C (without condensation and freezing Store the product in the original packing state.

Warranty and disclaimer

- Regal Joint is not responsible for any accident that is caused by incorrect or improper use of the product
- The warranty period of Regal Joint's product is one year after the date of delivery.
- For the defect of the performance or material within the warranty period. Regal Joint will supply an alternative product when Regal Joint permits in writing that Regal Joint is responsible for the defect. It should be noted that the range of warranty here is limited to Joint permits in writing that Hegal Joint is responsible for the defect. It should be noted that the range of warranty nere is limited to our products alone. Any damages including loss, damage, and injury that may occur directly or indirectly due to the malfunction of the product will be excluded from the warranty.

 If the alternative product is provided in advance upon request of the user and subsequent investigation of the defect has revealed that Regal Joint was not responsible for the defect, the cost of the alternative product will be charged.

 *Though the alternative product is basically the same product, there are cases where an equivalent product is supplied because of the
- reason of manufacturing.

 * Examples of defects for which Regal Joint is not responsible include:

 Use of the product outside the range of the description in the Operation Manual (latest version)


About the Operation Manual

- •It is not allowed to reprint and/or reproduce a part or all of this manual without a prior permission by us.
- •The description in this manual is subject to change without prior notice for performance improvement or other reasons.


 When using the Operation Manual, reference the latest version. The latest version is available in our website (URL http://www.rgl.co.jp/).
- The operation overview and specifications described in this manual is intended to explain the standard operation and characteristics of the product. Therefore, when using this product, perform appropriate physical design under the optimal conditions while considering external condit All efforts have been made to ensure the accuracy of all information in this manual. However, in the event you notice any unclear, incorrect, or insufficient part in this manual, contact us.
- * The shape and specifications are subject to change without prior notice to improve performance

Configuration and Dimensional Drawing

As shown in the figure below, a cover incorporating an electronic circuit (substrate) is mounted on the body that contacts liquid. On the top of the cover, the control panel to set the flow rate and temperature, and an LED display panel are placed.



Note: For the single unit fitting block, it is possible to fix its rear (by using two M4 countersunk head screws), to fix its bottom (by using four M4 hexagon socket head cap bolts), or to fix with a pipe, depending on the mounting dimensions



Specifications

Model		KSL-5L	KSL-10L	KSL-30L	KSL-50L	
Rated flow ra	te range	0.5-5.0 L/min	1.5-10.0 L/min	5.0-30.0 L/min	7.0-50.0 L/min	
Applicable	fluid		Industrial	water, water		
Detecting n	nethod		Karma	in vortex		
Fluid tempe	erature		0-90°C			
Ambient tem	perature		0-40°C (N	lo freezing)		
Temperature measu	rement range		0-1	00°C		
Accura	су		±2.0	%F.S.		
Max. operating	pressure		1.0	MPa		
Power supply	voltage *3		12 VDC±5% or 24 VDC±10%			
Current cons	umption	Max. 30 mA (Max. 70 mA with a 4 to 20 mA model)				
Cable	9	AWM20276 9 core/0.2 mm ² /500 mm				
Analog output	Flow rate	0-10 V or 4-20 mA/Pulse				
Analog output	Temperature	0-10 V or 4-20 mA				
Alarm output		Open collector A and B (Flow rate, temperature)				
Display method	Numerical value	Flow rate: 3-digit LED, temperature: 2-digit LED			t LED	
	Lighting	2-color alarm LED				
Certification, sta	ndard, etc.	RoHS Directive (SUS adapter specification only)				
Material of liquid co	ntacting part	Flow rate unit/PPS, temperature measurement unit/SUS304				
Material of conn	ecting part	SUS or BsBM (Ni-plated)				
Sealing O)-ring	Chloroprene rubber or fluorine rubber				
Pipe dian	neter		Rc3/8 or Rc1/2			
Weigh	nt		Approx. 390 g			

* 3 For the power supply voltage, either 12 VDC or 24 VDC may be selected when placing an order

Piping Flow meter unit M4 × 8 hexagon socket head cap bol rench (35 mm) ď Rc3/8 or Rc1/2 Piping adapter O-ring P-16 Hex wrench (3 mm) Single unit fitting block

- 1. Piping must be performed by screwing the pipe into the piping adapter or by using the Kantouch joint made by Regal Joint
- Caution on installing piping material When applying a wrench (35 mm), be sure to put it on the outer circumference of the piping adapter

ACAUTION Putting the wrench directly on the fitting block may cause a breakage of the fitting block.

- 3. The inner diameter of the piping adapter is that of an Rc3/8 screw or Rc1/2 screw.
- 4. The piping adapter is fixed on the fitting block by using four hexagon socket head cap bolts M4 × 8. Use a 3 mm hexagonal screw driver or L-Type wrench to mount and detach the adapter.

An O-Ring (Type P-16) is inserted into the sealing surface between the flow meter unit and the piping adapter.

Take care not to forget to insert it, not to twist it, and not to allow dust to enter inside.

WARNING

- Note that if the unit is installed without inserting an O-ring, water will be leaked.
- If water is very dirty when measuring water/industrial water, attach a filter to the pipe. Otherwise, sludge will accumulate in the fluid sensor, resulting in the malfunction of the sensor. (We will offer filters in response to your request.)

Wiring Method (interface)

Connect the cables to the relay terminal, connector, or the like by soldering or crimping. For connectors, the core wire sizes of #24 to #28 are recommended.

★ Warning Perform terminal processing for unused cables.

unction	of each cable]			
Color	Name	Characteristics	Output selection*4	Operation, usage
Red	Power supply +	24 VDC±10% 12 VDC±5%	One from two choices	DC power is supplied from the equipment. KSL has no power switch and the current flows to the unit the moment the power is supplied.
Black	Power supply -	GND		Common ground line. This single line serves as a common return for all other lines including the power supply.
White	Analog output Pulse output (flow rate)	0-10 V 4-20 mA Pulse output DPM	One from four choices	The flow rate is converted into an electric signal, which is sent to the equipment side.
Orange	Analog output (temperature)	0-10 V 4-20 mA	One from two choices	The water temperature is converted into an electric signal, which is sent to the equipment side.
Yellow	Alarm (flow rate)	Open-collector (A)*5	One from two choices	Alarm is reported to the equipment side when the flow rate exceeds the setting value. (A): ON when flow rate is equal to or greater than the setting value.
		Open-collector (B)		(B): ON when flow rate is smaller than the setting value.
Green	Alarm	Open-collector (A)*5	One from two choices the temperature exceeds the setting war (A): ON when temperature is equal to than the setting value.	Alarm is reported to the equipment side when the temperature exceeds the setting value.
Sieeii	(temperature)	Open-collector (B)		
Gray Blue Brown	Spare core			Spare core. Not used in ordinary circumstances.
For the c	able shown in "Outpu	it selection," one of th	nese specificat	ions is selected when placing an order.


*5 Alarm output (A) = OFF output, alarm output (B) = ON output

 ★ Warning - If cables not in use come in contact with each other or a cable comes in contact with external equipment, an accident or malfunction may occur. Be sure to insulate each cable before use.

- Power supply: (1) If a voltage exceeding the specifications is applied, the unit may be broken. (2) If cables are connected in the reverse polarity, the unit may be broken.

- Analog output
The unit may be broken if the output line is short circuited to the power supply.

[Method of applying a load] Standard method of applying the load resistance on the equipment side is shown below




Caution - When operating the unit under a relay load, use a relay with a diode (D) to prevent breakdown of the transistor due to a counter-electromotive force Because analog output is set to either voltage or current output at the factory setting, check the setting before use.


Output Signals

Output method Open-collector

Pulse shape See the figure above (pulse width fixed)

Remarks Relay load invalid






Open-collecto


Relay load invalid

Pulse shape See the figure above (pulse width varies

Operation Method



1. When DC power is supplied to the unit after connecting the interface cables, operation starts and enters the flow rate mode. (Because no power switch is provided, the unit starts by connecting to 24 VDC or 12 VDC.)



- 2. When (1) FLOW switch is pressed, (6) Display LED blinks and alarm setting is enabled.
- 3. By pressing (5) SET switch, the threshold value increases. When the target threshold value is reached, press (1) FLOW switch again. The threshold value is determined and the flow rate is
- When (5) SET switch is pressed while holding on (1) FLOW switch, the threshold value decreases.

Action when the actual flow rate exceeds the threshold value For alarm A in <Table 1>, (3) flow rate alarm display LED changes from red to green and the alarm signal of the cable is turned on. (When placing an order, the reverse polarity can also be selected.)

* If the flow rate excee following value, F is o KSL-5L 6 KSL-10L 12

ds the	(Definition of alarm ou	tput and
displayed.	_	
	Alarm	A
L/min	Measurement value	- ' '
	Equal to or greater	Green lamp
L/min	than the setting value	IS UN ON
L/min	and and octaing value	
L/min	Below the	Red lamp
L/IIIII	setting value	is ON
	ocurry value	V 0+

display LED) The definitions of the alarm output and display LED are specified in <Table 1> by Regal Joint.

We ask the customer to specify the desired alarm in accordance with the application when placing an order

* For the alarm output, ON indicates conductive and OFF indicates non-conductive in open-collector.
The alarm for the flow rate and that for the temperature can be set independently

Temperature setting

KSL-50L 60

1. Pressing (2) TEMP switch shifts the unit to the temperature mode. As shown in the figure at right, two digits are displayed and the unit is indicated in \mathcal{E} .

2. Pressing (2) TEMP switch again causes (6) Display LED to blink and the temperature alarm setting is enabled. 3. Pressing (5) SET switch increases the threshold value.

4. By pressing (2) TEMP switch, the threshold value is determined and the temperature indication is


Action when the water temperature exceeds the threshold value

For alarm A in <Table 1>, (4) Temperature alarm display LED changes from red to green and the alarm signal of the cable is turned on. (When placing an order, the reverse polarity can also be set.)

* The threshold can be set in a range from 0 to 99°C, but has no hysteresis.

Overrange di	F (100°C or more
Overrange un	0 (0°C or less)

Flow Rate Characteristics



- The flow rate characteristics are temperaturedependent as shown in the figure below.
- To maintain the accuracy, secure a straight-pipe length of 7D or more on the upstream side, and 5D or more on the downstream side. (D: Diameter, for 5L, D=4.1 mm; for 10L, D=5.8 mm; for 30L, D=10 mm; for 50L, D=12 mm)

- Do not change the pipe size significantly on the upstream side (by inserting an orifice and the like) when installing a pipe.

Install valves, branches, gauges and the like on the

Maintenance

[Removing the meter unit]

- (1) Turn OFF the power supply. (Because the power switch is not installed in this unit, remove the power
- (2) Loosen the four M4 screws (hexagonal socket head cap screws M4 × 8) with a 3 mm hexagonal screw driver or a hex wrench.
- (3) Shift the meter unit slightly toward the adapter side loosened in Step (2).
- (4) Because a gap is generated between the adapter and the meter unit, the meter unit can be pulled lowards the upper side of the unit block or toward the front. At this time, note that there is a possibility of flowing out of water in the pipe. In addition, be careful not to drop the O-rings placed on both sides

(5) To install the meter unit, follow the reverse procedure of removal

* If you have any questions on maintenance, contact us.

We are not responsible for any malfunction caused by disassembly or dismantling by the customer

Manufacturer: REGAL JOINT CO., LTD. 1-9-49 Onodai Minami-ku Sa

Kanagawa Japan 252 0331 Tel: +81-42 756 7411 Fax: +81-42 752 2004